



PRO BUSINESS RADIO

PX880

Up to 300,000 sqft / 25 Floor Range

Provides extended signal range with 2662 channel combinations.

22 Preset Channels

Channels are preset with Privacy codes to minimize unwanted interference from others.

VOX

Voice-activated transmission frees hands for other tasks.

VibrAlert®

Enhanced vibrating feedback to notify you of incoming transmissions.

Ultra Long Runtime

Can continue to use 18 hours (90% Standby / 5% Talk / 5% Listen).

360° Swivel Holster

Allows to rotate sideways for multiple positions.



Nothing Comes Close to a Cobra®

www.cobrawalkietalkie.com



PX880

Features

Benefits

UHF/FM	Ultra-clear long distance reception.
300,000 sqft / 25 Floor Range	Up to 300,000 sqft / 25 Floor range.(Range will vary depending on terrain and conditions.)
22 Preset Channels	22 channels have been preset with privacy codes to minimize unwanted interference from others.
121 Privacy Codes	38 CTCSS (Continuous Tone Coded Squelch System) codes and 83 DCS (Digitally Coded Squelch) codes provide a total of 121 privacy codes. 2662 privacy combinations are possible when the 22 channels are combined with the 121 privacy codes.
Ultra Long Runtime	Can continue to use 18 hours (90% Standby / 5% Talk / 5% Listen).
VOX (Voice Activated Transmission)	User's voice is detected and the radio transmits without the need to press any buttons, freeing the user's hands for other tasks. 5 VOX sensitivity levels allow user to select at which point the radio will detect their voice.
Call Alert	Provides an easily recognizable alert for incoming calls.
Roger Beep Tone	Confirmation tone indicates the completion of the user's transmission, and signals others it is clear to talk.
Key Lock	When activated, provides key pad security eliminating accidental channel changes.
Power Saver	A unique circuit extends the life of your batteries. If there are no transmissions within 10 seconds, the unit will automatically switch to battery save mode.
Auto Squelch	Automatically shuts off weak transmissions or unwanted noise due to terrain or range constraints.
LCD Display	Easy to view display provides the radio's status at a glance.
Speaker/Microphone/Jack	Allows use of wall charger, or earphone speaker/microphones (not included) for "hands-free" operation.
360° Swivel Holster	Secures your microTALK® radio while on the go.
No Licence or Service Fess	High quality band frequencies with no fees.
Volume Knob	Allow user to adjust any volume level easily and promptly.
Charging Dock	Reversible charging mechanism designed for most convenient drop-in charging.
VibrAlert®	Enhanced vibrating feedback to notify you of incoming transmissions.

Unit Specifications - General

Unit Dimension	170.3mm x 48.0mm x 59.5mm (6.70" x 1.89" x 2.34")						SKU#	PX880 BC
Unit Weight	232g. (8.18 oz.) without batteries						UPC	843677009132
22 Channels with Default Privacy Code	Channel	Privacy Code		Channel	Privacy Code		RF Output	1.8W
		Type	Number		Type	Number	Master Pack Qty	4
	1	CTCSS	1	12	DCS	77	Package Dimension	325mm x 89mm x 221mm (12.795" x 3.504" x 8.701")
	2	CTCSS	11	13	CTCSS	1	Package Weight	650g. (22.928 oz.)
	3	CTCSS	22	14	CTCSS	11	Batteries	1 pack of 2000mAH Li-ion Rechargeable Battery per radio
	4	CTCSS	33	15	CTCSS	22	Master Package Dimension	240mm x 338mm x345mm (9.449" x 13.307" x 13.583")
	5	DCS	1	16	CTCSS	33	Master Pack Weight	3.15kg. (111.111 oz.)
	6	DCS	11	17	DCS	1	*Specifications subject to change without notice* *All dimensions (H x W x L)*	
	7	DCS	22	18	DCS	11		
	8	DCS	33	19	DCS	22		
	9	DCS	44	20	DCS	33		
	10	DCS	55	21	DCS	44		
	11	DCS	66	22	DCS	55		

What is Included:



Cobra®, microTALK®, Nothing Comes Close to a Cobra®, and the snake design are registered trademarks of Cobra Electronics Corporation, USA.

Cobra Electronics Corporation™ is a trademark of Cobra Electronics Corporation, USA.

©2018 Altis Global Limited, Atlanta, GA USA



* Packaging is made from recyclable materials.

Nothing Comes Close to a Cobra®

PX880 SP 07/18